

PRODUCT DATASHEET

SMART+ ZB PLUG EU

SMART+ Plug | Plug with smart socket to control non smart devices with ZigBee technology



Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems

Product benefits

- Integrates conventional electric equipment into compatible smart home systems
- Enables switching of conventional light sources and other electric devices
- Simple connection of electric devices via standard socket

Product features

- Control via compatible smart home system, SMART+ Switch, SMART+ Switch Mini or on/off button on the device
- High switching power: up to 3,680 W / 16 A EU version and 2,990 W / 13 A UK version
- Functionality depends on used type of control
- Network protocol: ZigBee



TECHNICAL DATA

Electrical data

| | |
|---------------------|-------|
| Nominal voltage | 230 V |
| Operating frequency | 50 Hz |
| Mains frequency | 50 Hz |

Dimensions & weight

| | |
|----------------|-----------|
| Product weight | 111.000 g |
| Length | 84 mm |
| Width | 60 mm |
| Height | 60 mm |

Lifespan

| | |
|----------------------------|--------|
| Number of switching cycles | 100000 |
|----------------------------|--------|

Colors & materials

| | |
|---------------|-------|
| Product color | White |
|---------------|-------|

Temperatures & operating conditions

| | |
|---------------------------|--------------|
| Ambient temperature range | -20...+40 °C |
|---------------------------|--------------|

Additional product data

| | |
|----------------|---|
| Product remark | High switching power: up to 3,680 W / 16 A / Reset settings to default by switching the product on for five seconds and off for five seconds and repeating this five times. / Alternatively, press the reset button once for ten seconds. |
|----------------|---|

Capabilities

| | |
|----------------------------------|---|
| Compatible smart home technology | Philips Hue / Amazon Alexa / Google Assistant |
|----------------------------------|---|

Certificates & standards

| | |
|--------------------|------|
| Standards | CE |
| Protection class | I |
| Type of protection | IP20 |




EQUIPMENT / ACCESSORIES

- Control via app requires LIGHTIFY system (app and gateway) or other compatible Smart home system
-

Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Plug, after use in order to avoid them being accidentally switched on.
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Plug in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (for UK max. 13 A and for EU max. 16 A)

DOWNLOAD DATA

| DOWNLOAD DATA | |
|--|--|
|  | User instruction www UI SMART+ Plug |
|  | Declarations of conformity Declaration of Conformity Smart Home |
|  | Declarations of conformity EU Declaration of Conformity Zigbee Plug |

LOGISTICAL DATA

| Product code | Packaging unit (Pieces/Unit) | Dimensions (length x width x height) | Gross weight | Volume |
|---------------|------------------------------|--------------------------------------|--------------|----------------------|
| 4058075208315 | Folding box 1 | 61 mm x 96 mm x 154 mm | 199.00 g | 0.90 dm ³ |
| 4058075212848 | Shipping box 4 | 211 mm x 167 mm x 141 mm | 917.00 g | 4.97 dm ³ |

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.